

Applicable Screws

Nom Dia.

2~5mm

 $Y\theta$  (Linear Motion + Swivel Movement)

# SR565Y0-Z Screw Driving Robot **NITOMAN SR566Y0-Z**

### Equipped with AC servo Z-axis to the thrust control.

Easy to adjust the thrust force It is possible to set up the screw driving condition individually. Provide more suitable screw driving combined with KX/NX driver which is standard equipment.

### The CC-Link, DeviceNet<sup>TM</sup> or Ethernet as fieldbus network are available. (Option)

It is possible to install the interface for the CC-Link, DeviceNet<sup>TM</sup> or Ethernet as an optional extra.





SR565Y0-Z Example of machine configuration.

## **Thrust force control**

Optimum thrust control effectively prevents to damage to internal threads and cam-out.



#### **Recommended use**

- · Self tapping screw
- Prevention of bit camout •
- · Prevent thread breakage
- · Reduction of impact

## Outside dimensions (:mm)





#### [ SR566Y0-Z ]





### NITTOSEIKO CO., LTD. Assembly Machine Division / Shiroyama Plant **Global Sales Section**

2, Shiroyama, Ayabe city, Kyoto 623-0003, Japan URL : https://www.nittoseiko.co.jp/

## Specifications of robot

	Specifi	cations of	of robot	Inside of [ ] is the option.	
	Туре		SR565Y0	SR565Y0-Z	SR566Y0-Z
Screw driving unit	Number of axis to be controlled		Tow axes, simultaneously	Three axes, s	simultaneously
	Fastening torque control function		_	0	
	Applicable Screws *1 *2	Nom Dia.	Machine screw, Tapping screw 2~5mm (except M5 truss head screws)		
		Length	max. 18mm [25], min. screw head Dia.×1.1mm		
	Tightening torque *3		0.3~3.0N⋅m		
	Method of supplying screw		Blow feed or Picking up		
	Driver		KX driver, [NX driver]		
	Tightening stroke		100, [19	50】 mm	75, 125, 【175】 mm
	Screw holding system		Vacuum tube suction system		
	Fault detections		Faulty torque (faulty screw tightening)		
			Low screw (in screw feeder)		
			Faulty screw height	Faulty screw height	
			(proximity sensor)	ximity sensor) (Z-axis encoder pulse)	
Robot	Work envelope	Y-axis	200, 300, 400, 500mm		
		Turning radius	200, 250, 300mm 265, 315mm		
		θ-axis	180°		
	Maximum moving speed	Y-axis	1000mm/sec.		
		θ-axis	360°/sec.		
		Z-axis	-	720mm/sec.	
	Locating accuracy		±0.05mm		
Air pressure			0.4~0.5MPa		
Machine weight *4			Approximately 36Kg	Approximately 37Kg	
Screw feeder			FF503H		

Products will be built up based ore it can be used for one kind of screws only. Application range of screws will be changed by type of screw head, or size. \*2

Please contact us to make sure for it. \*3 The type of driver varies depending on target torque.

\*4 Weight will be changed by stroke, or type of driver. Please contact us to make sure for it.

#### Specifications of robot controller

Specifications of robot controller Inside of [] is the option					
Туре	RC5500-S				
Supply voltage	Single phase AC200~230V 50/60Hz				
Number of axis to be controlled	Six axes, max				
Robot movement	PTP control, Closed loop control				
Position feedback	Absolute encoder system (Battery backup:approximately five years)				
Serial port	RS-232C (for teaching pendant) Ethernet (100BASE-TX) RS-422 / RS-485				
Memory	SRAM : (Battery backup:approximately five years)				
External input *5 *6	Standard user port 16points [Additional 64 points outside ,max]				
External output *5 *6	Standard user port 16points [Additional 64 points outside ,max]				
Field network	【CC-Link, DeviceNet, Ethernet】				
Teaching method	MDI、Remote teaching, Direct teaching				
Point control	Work area : 40 points *7 ×100 types *7 Fixed area : 40 points				
Programming language	Ladder diagram & Textual language (About 40k steps)				
Robot program	Special motion language				
Outside dimensions(W×H×D)	200(250 * 7)×450×420mm (Not include a Rubber foot)				
Weight	Approximately 20kg				
	Handy Type touch panel				
Teaching pendant	(with Key switch, Emargency switch and Dead-man's switch)				
	Pendant can be used as manual control panel				
PC software	[MPE720 Ver.7] *8				

\*6 PNP type also available. (Need to specify at order timing. NPN or PNP.)

\*7 It depends on the specification. \*8 MPE720 Ver.7 is a software provided by YASUKAWA ELECTRIC CO.

Specifications and other matters are subject to modifications for performance improvements without notice.
Unique nouns like the product name indicated in this brochure are registered or not registered trademark of each company.
DeviceNet<sup>TM</sup> is a trademark of ODVA.
20220